

datavideo

PTR-10(T) Compatible Cameras

Model	Brand	Remote type (on Camera)	PTR-10 setup	Remote cable	Power Consumption	DC input
 PXW-Z280V	Sony	2.5mm (LanC)	LanC	G07620000132	24~31W	12V
 PXW-X200 (X280)	Sony	Sony 8-pin	BX-Lens	G07620000133	18~23W	12V
 PXW-Z190V	Sony	2.5mm (LanC)	LanC	G07620000132	22~29W	12V
 PXW-Z150	Sony	2.5mm (LanC)	LanC	G07620000132	6.3~6.6W	8.4V
 PXW-X160	Sony	2.5mm (LanC)	LanC	G07620000132	19.9~20.8W	19.5V*
 HNR-NX5R	Sony	2.5mm (LanC)	LanC	G07620000132	7.5~7.8W	8.4V
 HNR-NX100	Sony	2.5mm (LanC)	LanC	G07620000132	5.2~5.4W	8.4V
 AG-CX350PX	Panasonic	2.5mm (LanC)	LanC	G07620000132	11.5~17W	12V

* User needs to use camera's original power supply instead of being powered by PTR-10/10T

datavideo






PTR-10(T) Compatible Cameras

Model	Brand	Remote type (on Camera)	PTR-10 setup	Remote cable	Power Consumption	DC input
 AG-CX200MC	Panasonic	2.5mm (LanC)	LanC	G07620000132	11.5~17W	12V
 AJ-UPX360MC	Panasonic	2.5mm (LanC)	LanC	G07620000132	11.5~17W	12V
 GY-HC550/500	JVC	2.5mm (LanC)	LanC	G07620000132	24W	12V
 GY-HM171K	JVC	2.5mm (LanC)	LanC	G07620000132	7.6W	12V
 GY-HM606	JVC	2.5mm (LanC)	LanC	G07620000132	10W	12V
 GY-HM660	JVC	2.5mm (LanC)	LanC	G07620000132	12W	12V
 XF705	Canon	2.5mm (LanC)	LanC	G07620000132	20.8W	24V*
 XF405	Canon	2.5mm (LanC)	LanC	G07620000132	8.4W	8.4V

* User needs to use camera's original power supply instead of being powered by PTR-10/10T



PTR-10(T) Compatible Cameras

Model	Brand	Remote type (on Camera)	PTR-10 setup	Remote cable	Power Consumption	DC input
 XF305	Canon	2.5mm (LanC)	LanC	G07620000132	8.5~8.9W	8.4V
 XLH1	Canon	2.5mm (LanC)	LanC	G07620000132	7.8W	7.4V
 XHG1	Canon	2.5mm (LanC)	LanC	G07620000132	7.1~7.3W	7.4V
 BC-80	Datavideo	RS-422	RS-422	RJ-45		
 BC-200	Datavideo	RS-422	RS-422	RJ-45		

* User needs to use camera's original power supply instead of being powered by PTR-10/10T